



3246-60

PENCIL HiTESTER Instruction Manual



(3246-61)

600340344

Safety

Follow these precautions to ensure safe operation and to obtain the full benefits of the various functions.

⚠ DANGER


This instrument is designed to comply with IEC 61010 Safety Standards, and has been thoroughly tested for safety prior to shipment. However, mishandling during use could result in injury or death, as well as damage to the instrument. Using the instrument in a way not described in this manual may negate the provided safety features. Be certain that you understand the instructions and precautions in the manual before use. We disclaim any responsibility for accidents or injuries not resulting directly from instrument defects.

Measurement categories

This product complies with CAT IV (300 V), CAT III (600 V), CAT II (600 V) safety requirements.

To ensure safe operation of measurement products, IEC 61010 establishes safety standards for various electrical environments, categorized as CAT II to CAT IV, and called measurement categories.

CAT II: Primary electrical circuits in equipment connected to an AC electrical outlet by a power cord (portable tools, household appliances, etc.) CAT II covers directly measuring electrical outlet receptacles.



CAT III: Primary electrical circuits of heavy equipment (fixed installations) connected directly to the distribution panel, and feeders from the distribution panel to outlets.

CAT IV: The circuit from the service drop to the service entrance, and to the power meter and primary overcurrent protection device (distribution panel).

Using a measurement instrument in an environment designated with a higher-numbered category than that for which the instrument is rated could result in a severe accident, and must be carefully avoided.

Use of a measurement instrument that is not CAT-rated in CAT II to CAT IV measurement applications could result in a severe accident, and must be carefully avoided.

Safety Symbol

	In the manual, the ⚠ symbol indicates particularly important information that the user should read before using the product. The ⚠ symbol printed on the product indicates that the user should refer to a corresponding topic in the manual (marked with the ⚠ symbol) before using the relevant function.
	Indicates a double-insulated device.
	Indicates AC (Alternating Current).
	Indicates DC (Direct Current).
	Indicates DC (Direct Current) or AC (Alternating Current).

Symbols for Various Standards

	This symbol indicates that the product conforms to safety regulations set out by the EC Directive.
	WEEE marking: This symbol indicates that the electrical and electronic appliance is put on the EU market after August 13, 2005, and producers of the Member States are required to display it on the appliance under Article 11.2 of Directive 2002/96/EC (WEEE).

- ⚠ DANGER** Indicates that incorrect operation presents an extreme hazard that could result in serious injury or death to the user.
- ⚠ WARNING** Indicates that incorrect operation presents a significant hazard that could result in serious injury or death to the user.
- ⚠ CAUTION** Indicates that incorrect operation presents a possibility of injury to the user or damage to the product.
- NOTE** Advisory items related to performance or correct operation of the product.

Usage Notes



This manual contains information and warnings essential for safe operation of the product and for maintaining it in safe operating condition. Before using the product, be sure to carefully read the following safety notes.

⚠ WARNING

- To avoid electric shock, do not allow the product to get wet, and do not use it when your hands are wet.
- Do not use the product where it may be exposed to corrosive or combustible gases. The product may be damaged or cause an explosion.
- To avoid electric shock when measuring live lines, wear appropriate protective gear, such as insulated rubber gloves, boots and a safety helmet.

⚠ CAUTION

- Do not store or use the product where it could be exposed to direct sunlight, high temperature or humidity, or condensation. Under such conditions, the product may be damaged and insulation may deteriorate so that it no longer meets specifications.
- This product is not designed to be entirely water- or dust-proof. To avoid damage, do not use it in a wet or dusty environment.
- This product is designed for indoor use, and operates reliably from 0°C to 40°C.
- To avoid damage to the product, protect it from vibration or shock during transport and handling, and be especially careful to avoid dropping.
- Do not use the product near a device that generates a strong electromagnetic field or electrostatic charge, as these may cause erroneous measurements.
- To avoid damaging the test leads, do not bend or pull the leads.
- If the protective functions of the product are damaged, either remove it from service or mark it clearly so that others do not use it inadvertently.

NOTE

- Accurate measurement may be impossible in the presence of strong magnetic fields, such as near transformers and high-current conductors, or in the presence of strong electromagnetic fields such as near radio transmitters.
- To avoid battery depletion, turn the Function Selector OFF after use (the Auto Power Save feature consumes a small amount of current).
- The indicator appears when battery voltage becomes low. Replace the batteries as soon as possible.
- To avoid corrosion from battery leakage, remove the batteries from the product if it is to be stored for a long time.

Parts Names

HOLD Button


- Holds the measurement value (**HOLD** lights up).
- Cancels the Auto-Power Save function (APS). (Turn on the power while pressing **HOLD**.)
- Turns on the light. (Press **HOLD** for at least 1 second.)

Select Button

- Selects DC/AC (V) (Press the select button for at least 1 second in manual ranging mode.)
- Selects mode (>>>/<<). (Press the select button for at least 1 second in manual ranging mode.)
- Changes to the manual range function. (Turn on the power while pressing the select button.)
- Selects range (in manual ranging mode).


Penlight

Hole for attaching your own strap for greater portability.



- OFF** Power Off (Power is turned ON in any position other than OFF.)
 - DC voltage function (DCV)
 - AC voltage function (ACV)
 - Resistance function
 - Continuity Check function
 - Diode Check function
- Select with the select button
- Select with the select button

LCD Display



Handling the Sleeve of test lead



⚠ WARNING

Removable sleeves can be attached to the metal pins at the ends of the test leads. To prevent a short circuit accident, be sure to use the test leads with the sleeves attached when performing measurements in the CAT III and CAT IV measurement categories. Remove the sleeves from the test leads when performing measurements in the CAT II measurement category. For details on measurement categories, see "Measurement categories") in the instruction manual.


⚠ CAUTION

- The tips of the metal pins are sharp, so take care not to injure yourself.
- When performing measurements with the sleeves attached, be careful to avoid damaging the sleeves.
- If the sleeves are inadvertently removed during measurement, be especially careful in handling the test leads to avoid electric shock.

Handling the Cap (yellow) of Pencil HiTester

⚠ CAUTION

- Observe the following to avoid damage to the product.
- Do not pull the cap with excessive force.
- Replace the cap when not using the product.



When using the 3246, remove the cap and securely fasten the cap to the rear, as shown in the figure.

When removing the cap, be careful not to prick your finger with the tip of the lead.

Handling the Test Leads



When storing the 3246-60 test lead (black), be sure to wind the lead around the protrusion on the rear.

Specifications

General

Measurement Method	Dual integration
AC Measurement System	Average rectifying measurement
Function	DC voltage (DCV), AC voltage (ACV), Resistance (Ω), Continuity check (⚡), Diode check (➡)(Forward direction/Reversed direction judgment only)
Additional Function	Auto Range function, Manual Range function, Hold function, Auto Power Save function (APS), Battery-Life Warning function, Overflow Warning function, Penlight function, LCD Backlight function
Display Type	TN type LCD, 1/4 duty, dynamic drive

