# HIOKI **CLAMP ON SENSOR**

#### INSTRUCTION MANUAL

September 2006 Revised edition 5 Printed in Japan 9661A980-05 06-09H

#### HIOKI E.E. CORPORATION

#### Introduction

Thank you for purchasing the HIOKI "9661 CLAMP ON SENSOR." To obtain maximum performance from the product, please read this manual first, and keep it handy for future reference

#### **Initial Inspection**

When you receive the product, inspect it carefully to ensure that no damage occurred during shipping. If damage is evident, or if it fails to operate according to the specifications, contact your dealer or Hioki representative.

#### **Preliminary Checks**

- · Before using the product the first time, verify that it operates normally to ensure that the no damage occurred during storage or shipping. If you find any damage, contact your dealer or Hioki representative.
- Before using the product, make sure that the insulation on the cables is undamaged and that no bare conductors are improperly exposed. Using the product in such conditions could cause an electric shock, so contact your dealer or Hioki representative for repair.

#### **Maintenance and Service**

- To clean the product, wipe it gently with a soft cloth moistened with water or mild detergent. Never use solvents such as benzene, alcohol, acetone, ether, ketones, thinners or gasoline, as they can deform and discolor the case.
- If the product seems to be malfunctioning, contact your dealer or Hioki representative.


	HIOKI
DECLARATIO	N OF CONFORMITY
Manufacturer's Name: HI	OKI E.E. CORPORATION
	81 Koizumi, Ueda, Nagano 386-1192, Japan
Product Name: CLAM	P ON SENSOR
Model Number: 9661	
The above mentioned propoduct specifications:	duct conforms to the following
Safety: EN61010-2	-032:2002
ClassA e	
Equipmei locations	nt intended for use in industrial
Supplementary Information	on:
	nplies with the requirements of 73/23/EEC and the EMC
	HIOKI E.E. CORPORATION
15 September 2006	Tatsuyoshi Yoshiike
	President
	9661A999-02

## **Specifications**

Accuracy guaranteed for one year at 23±5°C (73±9°F), 80%RH or less., opening and closing of the sensor: maximum 10,000 times Rated primary 1 mV AC/A Output voltage ±0.3% rdg.±0.01%f.s. (f.s.:500 A, 45 Hz - 66 Hz, at core center) Amplitude accuracy Phase accuracy Within ±0.5° at 45 Hz - 5 kHz Amplitude frequency Within ±1% at 40 Hz - 5 kHz characteristics (deviation from amplitude accuracy) Effect of conductor Within ±0.5% (deviation from center) Effect of external 0.1 A equivalent or lower (in an AC electromagnetic field 550 A continuous (at 45 - 66 Hz, ambient temperature 50°C)

Frequency-based derating characteristics

Maximum input



		0 ( )
	Operating Environ- ment	Indoors, altitude up to 2000 m (6562-ft.)
	Storage Temperature & Humidity	-10 to 60°C(14 - 140°F), 80%RH or lower (non-condensating)
	Operating Temperature & Humidity	0 to 50°C (32 - 122°F), 80%RH or lower (non-condensating)
	Maximum rated voltage to earth	600 V rms or lower
	Dielectric strength	5312 V rms for 15 seconds (between electric circuit and core
	Temperature coefficien	t0.02%rdg/°C

Safety Applicable Standards EMC	EN61010-2-032:2002, Type A current sensor Measurement Category III, Pollution Degree 2 (Anticipated Transient Overvoltage: 6000 V) EN61326:1997+A1:1998+A2:2001+A3:2003 (Class A)
Measurable conduc-	(4.04") == l===

tor diameter	φ46 mm (1.81") or less
Cable length	Approx. 3 m (118.11")
Dimensions	Approx. 78W x 152H x 42D mm (3.03"W x 5.94"H x 1.65"D) (excluding protrusions)
Mass	Approx. 380 g (13.4 oz.)
Accessory	Instruction Manual
f.s. : maximum displa	y value or scale length

rdg.: reading value (The value currently being measured and indicated on the measuring product)

# Safety

Follow these precautions to ensure safe operation and to obtain the full benefits of the various functions

### **▲** DANGER

This product is designed to conform to IEC 61010 Safety Standards, and has been thoroughly tested for safety prior to shipment. However, mishandling during use could result in injury or death, as well as damage to the product. Be certain that you understand the instructions and precautions in the manual before use. We disclaim any responsibility for accidents or injuries not resulting directly from product defects.

#### Safety Symbol

<u> </u>	In the manual, the $ rianlge \Lambda$ symbol indicates particularly important information that the user should read before using the product. The $ rianlge \Lambda$ symbol printed on the product indicates that the user should refer to a corresponding topic in the manual (marked with the $\overline{\Lambda}$ symbol) before using the relevant function.	
	Indicates a double-insulated device.	
~	Indicates AC (Alternating Current).	
4	Indicates that the instrument may be connected to or disconnected from a live circuit.	

The following symbols in this manual indicate the relative importance of cautions and warnings

A DANGER Indicates that incorrect operation presents an extreme hazard that could result in serious injury or death to the user. Indicates that incorrect operation presents a significant hazard that

CAUTION could result in serious injury or death to the user.

Indicates that incorrect operation presents a possibility of injury to the user or damage to the product


NOTE Advisory items related to performance or correct operation of the product.

#### Measurement categories (Overvoltage categories)

This product complies with CAT III safety requirements To ensure safe operation of measurement products, IEC 61010 establishes safety standards for various electrical environments, categorized as CAT I to CAT IV, and called measurement categories. These are defined as follows.

CAT I: Secondary electrical circuits connected to an AC electrical outlet through a transformer or similar device.

CAT II: Primary electrical circuits in equipment connected to an AC electrical outlet by a power cord (portable tools, household appliänces, etc.) CAT III: Primary electrical cir-



cuits of heavy equipment (fixed installations) connected directly to the distribution panel, and feeders from the distribution panel to outlets.

CAT IV: The circuit from the service drop to the service entrance, and to the power meter and primary overcurrent protection device (distribution panel). Higher-numbered categories correspond to electrical environments with greater momentary energy. So a measurement device designed for CAT III environments can endure greater momentary energy than a device designed

Using a measurement product in an environment designated with a highernumbered category than that for which the product is rated could result in a severe accident, and must be carefully avoided Never use a CAT I measuring product in CAT II, III, or IV environments.

The measurement categories comply with the Overvoltage Categories of the IEC60664 Standards

# **Usage Notes**

This manual contains information and warnings essential for safe operation of the product and for maintaining it in safe operating condition. Before using the product, be sure to carefully read the following safety notes.

#### **⚠** DANGER

· To avoid short circuits and potentially life-threatening hazards, never attach the product to a circuit that operates at more than the 600 V AC.



This product should only be connected to the secondary side of a breaker, so the breaker can prevent an accident if a short circuit occurs. Connections should never be made to the primary side of a breaker, because unrestricted current flow could cause a serious accident if a short circuit occurs.

#### 

- To avoid electric shock, do not allow the product to get wet, and do not use it when your hands are wet.
- To avoid electric shock when measuring live lines, wear appropriate protective gear, such as insulated rubber gloves boots and a safety helmet.
- Note that the product may be damaged if current exceeding the selected measurement range is applied for a long time.


#### $\triangle$ Caution

- Do not store or use the product where it could be exposed to direct sunlight, high temperature or humidity, or condensation. Under such conditions, the product may be damaged and insulation may deteriorate so that it no longer meets specifications.
- Be careful to avoid dropping the product or otherwise subjecting them to mechanical shock, which could damage the mating surface es of the core and adversely affect measurement.
- Keep the clamp jaws and core slits free from foreign objects, which could interfere with clamping action.
- Avoid stepping on or pinching the cable, which could damage the cable insulation.
- To avoid damaging the cables, do not bend or pull the cables.

Accurate measurement may be impossible in the presence of strong magnetic fields, such as near transformers and high-current conductors, or in the presence of strong electromagnetic fields such as near radio transmitters.

## Parts Names

The 9661 is a voltage-output-type clamp-on sensor



# **Measurement Procedur**

### $\triangle$ Caution

- When disconnecting the BNC connector, be su lock before pulling off the connector. Forcibly pull without releasing the lock, or pulling on the cable
- To prevent damage to the connected instruments er connect or disconnect a sensor while the pow

auide

Ŵ

Attach the clamp around only one conductor. Single three-phase (3-wire) cables clamped together will reading.

Flectric

Current direction indicator

Position the clamp with the current

direction indicator pointing toward the load side. (If installed in the opposite direction, the phase deviates 180



Connect the BNC connector.

Clamp the conductor.

Connector BNC connector grooves





grooves w auide proi the conne lock the co



2. Open the only one clamp cer rent directi ing toward

Make sure closed.

To remove the tor, turn the c clockwise and

ide.



ales@calcert

യ -wire) or uce any

ത

nnector nnectornd turn

nd hold

at the he curor point-

core is

O ounter