

## CAT III compatible, High-Voltage and True-RMS Data Logger

High-speed High-Voltage Isolated 4 channel Measurements

**midi LOGGER**


# HV GL2000

**NEW**


- 4ch High Speed Simultaneous Sampling
- CAT III 600V Compatible
- Measure AC 600 V Measurement with True-rms
- Built-in High-capacity RAM (4 M sampling/ch)
- and Flash memory (4 GB)
- Large Easy-to-read 7-inch LCD

### Typical applications


- Flow rate and temperature test in water heaters




- Performance test of inverters for air conditioner



- Thermal insulation performance measurement of residential housing




- Voltage and temperature measurement of generators



# High speed 1 MS/s simultaneous sampling with isolated input

GL2000 is equipped with an isolated input mechanism to protect signals from interferences caused by noise from other channels. 16-bit A/D converter adopted to achieve hi-speed and hi-resolution measurement.



## Simultaneous sampling

**Sampling interval : 1 μs to 1 min (in steps of 1, 2, 5)**

GL2000 utilizes simultaneous sampling to eliminate slowdown in sampling rate by using multiple A/D converters in simultaneous sampling method.

Four individual A/D converters in each channel sustains the maximum sampling speed for all four channels to measure high speed rapid voltage fluctuation and multi-channel vibration measurement.

## External sampling function

**Maximum input frequency : 100 kHz**

Sampling of the logger is performed in sync with an external device using an external signal input.

\* B-513 Input/Output cable for GL is required.

## Multifunction input with CAT III measurement category

■ Voltage, temperature, humidity, logic and pulse measurements can all be taken simultaneously in high speed.

### Pulse/Logic

Pulse : 4ch (Instant, Accumulating, RPM)

Logic : 4ch

\* Select either Pulse or Logic.

\* Required input/output cable for GL (B-513 option).

### Screw terminal (size M3.5)

Thermocouple : K, J, E, T, R, S, B, N, W(WRe5-26)

Humidity : 0 to 100 %

\* Required humidity sensor (B-530 option).

### Isolated BNC connector

**CAT III 600 V**


Voltage (DC) : 20 mV to 1000 V, 1-5 V

Voltage (RMS) : 10 mV to 1000 V rms

\* Maximum rated safety voltage : ± 600 V DC or 600 V rms

\* Connection can be made individually to BNC or screw terminal. BNC and screw terminal are connected to the same channel.

■ CAT III 600 V is compatible with measuring power supply circuit in an equipment that captures power directly from the distribution panel.



■ Measures abnormalities in a repeated waveform by effectively measuring the corresponding RMS value

■ In 1000 Vrms range, Crest Factor is up to 1.41

\* Maximum rated safety voltage : 600 V rms, Peak voltage: 850V

■ In other range, Crest Factor is up to 2.0

### Instantaneous value meas.




### RMS (effective value) meas.



## Scaling (Engineering unit) function

Measured voltage value can be converted to a specified engineering unit. The value can be displayed with the physical measurement value of the sensor and be saved into the data file with the converted values.



## Calculation function between channels

Four arithmetic operations (Addition, subtraction, multiplication and division) are available using two analog input channels.

\* Data can be saved only in GBD file format.

### Example

$$CH2 = CH3 * CH1$$

(CH2 is a value obtained by multiplying the values of CH3 and CH1)

\* Value of calculated results are displayed and saved into data file.

## Trigger function

The trigger in this unit has multiple functions including level trigger of input signal value for each channel.

**Trigger action** Start or stop capturing data by triggering

**Trigger source** Off, Measured signal level, Alarm, External, Scheduled time, Scheduled day, Elapsed time  
\* When trigger is used for starting action, level of measured signal can be set for each channel.

**Threshold** Analog input : High or Rising, Low or Falling, Window-in, Window-out  
Logic input : H or L (4-channel signal pattern)  
Pulse input : High or Rising, Low or Falling, Window-in, Window-out  
Combination : Level OR, Level AND, Edge OR, Edge AND

## Alarm function & signal output

Threshold of an alarm can be set for each channel. When an alarm occurs, notification is sent by following methods.

### Alarm threshold

Analog input : High, Low, Window-in, Window-out

Logic input : H or L (signal in each channel)

Pulse input : High or Rising, Low or Falling, Window-in, Window-out

### When alarm is detected

Display to screen (Digital value of alarm's origin channel is displayed in red)

Save alarm information to measurement data file

Output alarm signal

Number of channel : 4 channels (Output channel can be arranged to each source channel in OR condition.)

Signal type : Open collector (pull-up to 5 V with 10 kΩ resistor), maximum load is the 24 V and 100 mA.


\* Requires Input/Output cable for GL series (B-513 Option).

# Large Easy-to-read 7-inch LCD

Monitor data in multiple methods in addition to digital value display and full waveform display screen.

## Y-T waveform monitor screen


Displays data with analog waveform and digital value. Screen can also be split into 1, 2, 4 or 8 zones to display the channels in different zones.



## Digital monitor screen


Displays current data in digital value and results of real time statistical calculation. (Function : Maximum, Minimum, Peak-to-peak, and Average)

When displays only current data, it can be shown in 1, 2, 4 or 8 zones.



## Past waveform monitor screen

Display the past part of the data while capturing data. Execute without stopping measurement and also scroll past data. Data screen can be switched with past and current.



## XY graph monitor screen

Emulates the classic XY chart recorder. Also supports features for pen up/down and position movement.



## Quick and Easy Set Up Process

Simple operation with cursor and enter keys, and menu-driven operation with six pre-set menu screens: AMP, DATA, DISP, TRIG, I/F (Interface) and OTHER.

### Cursor keys


Move between items on the setting screen and move the cursor on the waveform screen.

### ENTER key

Determine the item and value selected with the menu.

### FUNCTION (FUNC) key

Execute the specified function with this shortcut button. Frequently used function can be preset.



### Only 6 screens

AMP	DATA	DISP
TRIG	I/F	OTHR

### Free-running function

The input signal being captured in real time can be monitored on the measurement or setting screen even if recording has not initiated. The measurement voltage range can be set while watching the waveform.



## Other helpful functions

Delivers reliable measurements out at a location with unstable power supply.

Equipped with three types of options for power source, AC adapter, DC input, and battery pack. With a battery pack, GL2000 runs continuously for approximately 3 hours. If an AC power failure occurs, it will automatically switch from the AC adapter to the battery pack. Additionally, when the voltage of the battery pack reaches low, measurement is automatically stopped after saving the data file preserving the accumulated data. (Requires two battery packs (B-569 option) installed.)

Instrument is in compliance with JIS Vibration Test Method for Automobile Type 1 Class A. (Vibration durability test: 5 m/s<sup>2</sup>)

### Carrying case (B-581)

Portable case to store GL2000 and signal input cables for easy handling.

coming soon

### Cover (B-579)


Protect the main body from cosmetic damages and minor impacts. GL2000 is shipped with cover attached.



\* The cover is not to protect from hard impact.

# Supports large built-in RAM (4MS/ch) and built-in Flash (4 GB)

Long term recording is made possible with 4 M samples/ch built-in RAM and 4 GB built-in Flash memory. It supports both USB Flash memory and SD Card memory to be used as external storage devices for recorded data for certain sampling intervals.



## Approximate recording time

■ 4 channels of analog input. ■ Data is saved as a GBD file.

Memory type	Data capacity	1MS/s(1μs)	100kS/s(10μs)	1kS/s(1ms)	1S/s(1s)
Built-in RAM	4 M samples/ch	4 seconds	40 seconds	66 minutes	46 days
Built-in Flash memory	3.9 GB	N/A	N/A	3 days 19 hrs.	Over 1 year
External memory (SD/USB Flash memory)*	4 GB	N/A	N/A	4 days 3 hrs.	Over 1 year

■ 4 channels of analog input with 4 channels of Pulse input. ■ Data is saved as a GBD file.

Memory type	Data capacity	1MS/s(1μs)	100kS/s(10μs)	1kS/s(1ms)	1S/s(1s)
Built-in RAM	4 M samples/ch	4 seconds	40 seconds	66 minutes	46 days
Built-in Flash memory	3.9 GB	N/A	N/A	1 days 12 hrs.	Over 1 year
External memory (SD/USB Flash memory)*	4 GB	N/A	N/A	1 days 15 hrs.	Over 1 year

\* When using 8 GB or larger memory, the size of data file will be up to 4 GB. The Relay mode enables extended recording time.

## Convenient Data Recording Functions

### Memory division function

Built-in RAM


Built-in Flash

SD card

USB memory

#### Single block

When multiple measurements are executed, the captured data is overwritten in memory block 1.



#### Divided into 8 blocks

When multiple measurements are executed, recorded data is stored in the next memory block.



### Relay mode

Built-in RAM

Built-in Flash

SD card

USB memory

Save data to multiple files with specified capturing time or file size (up to 4 GB) until recording data is stopped.



Maximum sampling speed :  
1 kS/s (interval 1 ms) with GBD format,  
100 S/s (interval 10 ms) with CSV format

### Data backup and hot swaps

Built-in RAM

Built-in Flash

SD card

USB memory

The recorded data can automatically save to other storage device at specified regular intervals during data capture. (Maximum sampling speed: 1 kS/s (interval 1 ms) with GBD format, 100 S/s (interval 10 ms) with CSV format)

When the backup destination is set to a SD Flash memory card or a USB Flash memory device, memory device can be exchanged before the memory capacity becomes full using the key operation.

### Auto save function

Built-in RAM

Built-in Flash

SD card

USB memory

Recorded data saved in a built-in RAM is automatically copied as data file to a built-in Flash memory, SD Flash memory card or USB Flash memory with auto save function. An SD Flash memory card or a USB Flash memory can be used as a backup location when using the built-in RAM. The process will prevent losing any data captured in the built-in RAM by any overwrite or power cycles.

## Approximate recording time

■ 4 channels of analog input. ■ Data is saved as a GBD file.

Memory type	Data capacity	1MS/s(1μs)	100kS/s(10μs)	1kS/s(1ms)	1S/s(1s)
Built-in RAM	4 M samples/ch	4 seconds	40 seconds	66 minutes	46 days
Built-in Flash memory	3.9 GB	N/A	N/A	3 days 19 hrs.	Over 1 year
External memory (SD/USB Flash memory)*	4 GB	N/A	N/A	4 days 3 hrs.	Over 1 year

■ 4 channels of analog input with 4 channels of Pulse input. ■ Data is saved as a GBD file.

Memory type	Data capacity	1MS/s(1μs)	100kS/s(10μs)	1kS/s(1ms)	1S/s(1s)
Built-in RAM	4 M samples/ch	4 seconds	40 seconds	66 minutes	46 days
Built-in Flash memory	3.9 GB	N/A	N/A	1 days 12 hrs.	Over 1 year
External memory (SD/USB Flash memory)*	4 GB	N/A	N/A	1 days 15 hrs.	Over 1 year

\* When using 8 GB or larger memory, the size of data file will be up to 4 GB. The Relay mode enables extended recording time.

### Ring mode

Built-in RAM

Built-in Flash

SD card


USB memory

#### Number of capturing data

1000 to 10000000 data

\* When using built-in RAM, 10 to 400000 data

Example :  
Number of capturing data : set to 5000 points



Always save the recent 5000 data  
(The oldest data is overwritten by the new data.)

Maximum sampling speed :  
1MS/s (interval 1 μs) in built-in RAM,  
1kS/s (interval 1 ms) with GBD format in another device,  
100S/s (interval 10 ms) with CSV format in another device

### Save & replay data in CSV format

Built-in RAM

Built-in Flash

SD card

USB memory

Capturing data in CSV format

Replay

Built-in Flash, SD Flash memory card,  
USB Flash memory device



Excel can display  
captured data without file  
format conversion.

### Search function

Built-in RAM

Built-in Flash

SD card

USB memory

The search function can locate a specific value within the captured data as well as finding abnormal values within data of a long-recorded file.

#### Search content

Search for analog signal levels, logic signal pattern,  
pulse signal levels or alarm point in captured data.

##### Analog signal channel

Signal levels in each channel

■ Search mode: raising, falling, window-in, window-out

##### Logic signal channel

Signal level (H or L) in each channel

##### Pulse signal channel


Signal levels in each channel

■ Search mode: raising, falling, window-in, window-out

##### Alarm

Alarm detected point on selected alarm signal output channel

# Equipped with Ethernet (LAN) and USB interface to communicate with PC



\* This interface is for connecting directly to PC only.

Measurement method	Data file format in PC	Available sampling speed
<b>Real time measurement</b> Transfer data captured with GL2000 to PC.	Binary or CSV format	1 ms to 1 min
<b>Memory measurement</b> Transfers data to PC after completed capturing data to built-in RAM with GL2000.	Binary format	1 µs to 1 min

\* Captured data can be saved with storage device on GL2000 and PC simultaneously.

## Convenient function with LAN (Ethernet interface) capability

When GL2000 is connected to LAN using the Ethernet interface, networked computer can monitor real-time measured value, transfer files, and change set ups without using application software (GL980\_2000-APS software).


### Web server function

GL2000 can be controlled externally via a network on the WEB browser, which also supports real-time monitoring and ability to use the menu buttons.




### FTP server function

File in available storage device on GL2000 except built-in RAM can be transferred or deleted from the PC.




### NTP client function

The clock on the GL2000 is periodically synchronized with the NTP server.



### Email sending function

Send information when alarm occurs, or when battery is low, or when communication speed drops, or to notify when the space becomes limited on the storage device by an e-mail to specified address. Information can also be sent periodically by settings.



## USB Drive Mode to Easily Transfer Files to PC

### USB drive mode

The USB drive mode function allows simple data transfer to the PC from built-in Flash memory and SD Flash memory card which acts as USB Flash drive on GL2000. It also allows to add, remove, and delete files from storage device on GL2000 from PC file browsing explorer.

\* Built-in Flash and SD, except USB memory device.



Start USB drive mode by turning the power on while pressing START/STOP key.

Move files by drag & drop feature in PC.

## PC measurement with standard PC software included (GL980\_2000-APS)

### Multiple measurement screens including Y-T waveform, XY chart


#### Y-T display

Recorded signal is displayed in waveform (Y-T) and digital value for each channel.




#### Y-T display (Zone mode)

Screen is divided into multiple zone, and channels can be assigned to each zone.




#### XY display

Four groups of XY charts are displayed.



### Easily Connect to the GL2000 with Quick Set Up Conditions



### Convenient features from the GL980\_2000-APS software

#### File combine and bind function

##### Superimpose

Data or file recorded on another unit or time can be imported as additional channels when using a SUPERIMPOSE function.

##### Link

Captured data in multiple files are connected and saved as new file. It is helpful in reviewing data captured with relay mode.

\* Measurement parameters of each file must be the same.

#### Direct Excel function

The GL980\_2000-APS software executes recorded data into a file on PC in real time and exports to a specified Excel file at the same time.

This is a valuable tool in creating report requiring post-process calculation with Excel software.

#### Printing function

The waveform of the playback data can be printed using a default printer. Printing range of the waveform can be set between cursors or all waveforms.

## Advanced software GL-Connection (version 2.0)


### The high-performance software GL-Connection is included as an accessory

#### Major features

- Supports connection with other GL units (\*) simultaneously
- Supports up to 20 GL units (\*)
- Screen division function: 4 screens
- FFT analysis function

\* GL220, GL240, GL820, GL840 series, GL900 series, GL7000 series, GL980 and GL2000 can be connected.

\* Ethernet (LAN) and USB can be mixed for connection between GL unit and PC.



Main unit specifications	
Item	Description
Display (LCD)	Size 7-inch TFT color LCD (WVGA: 800 x 480 dots)
	Information Waveform in Y-T with digital values, Enlarged waveforms, Digital values and Real-time statistical result values, XY graph
	Language English, French, German, Spanish, Russian, Chinese, Korean, Japanese
Interface to PC	Type Ethernet (10 BASE-T/100 BASE-TX), USB2.0
	Function Data transfer to PC (up to 1 ms sampling), Control command to GL2000
	Ethernet functions Web server function, FTP server function, NTP client function, DHCP client function, Email send function
USB function	USB mode (File transfer and deletion from built-in flash and SD on GL2000)
	Trigger action Start or stop capturing data by triggering
	Trigger Start Off, Measured signal, Alarm, External, Scheduled time, Elapsed time
Trigger function	source Stop Off, Measured signal, Alarm, External, Scheduled time, Elapsed day, Elapsed time
	Combination Level OR, Level AND, Edge OR, Edge AND
	Threshold Analog (*1) High or Low in level mode, Rising or Falling in edge mode, Window-in, Window-out
Trigger function	Logic H or L (4-channel signal pattern)
	Pulse High or Rising, Low or Falling, Window-in, Window-out
	Repeat action Off, On (Re-armed automatically)
Trigger hold out	Hold off repeat action in specified period
	Mode Previous start to next start, previous stop to next start
	Time zero second (no hold off) to 9999 hrs. 59 min. 59 sec
Defection accuracy	± 0.5 % of measurement range
	Pre-trigger Up to the number of capturing data points (max. 4000000) specified in built-in RAM (only when built-in RAM is used)
	Alarm action Displays and outputs a signal when alarm is detected
Alarm function	Threshold Analog input High, Low, Window-in, Window-out
	Logic input H or L (signal in each channel)
	Pulse input High or Rising, Low or Falling, Window-in, Window-out
Combination	OR (Source channel can be assigned with OR condition to output port)
	Detection cycle Link with analog sampling
	Alarm holding On or Off
Detection accuracy	± 0.5 % of measurement range
	Built-in RAM Four million samples for each channel
	Memory partition 4 M samples x 1 bank, 2 M sample x 2 banks, 1 M samples x 4 banks, 500 k samples x 8 banks
Storage device	Capturing data points Specified 10 to 4000000
	Data type Captured data
	Auto-save Transfer captured data to other devices after capturing is completed (It can be enabled or disabled)
Built-in Flash	4 GB (for capacity of data: approx. 3.9 GB)
	Data type Captured data, Condition settings, Screen copy
	External USB (*2) Support USB Flash memory device (*3) by USB2.0 Type A port, Single port, No memory capacity limit
External SD CARD (*2)	Data type Captured data, Condition settings, Screen copy
	External SD CARD (*2) Support SDHC memory card (up to 32 GB) by SD Card slot, Single slot
	Data type Captured data, Condition settings, Screen copy
Capturing mode	Mode Off (Normal), Ring, Relay
	Off (Normal) Save data between start to stop
	Ring (*4) Save most recent data of specified number
Sampling	Destination Built-in RAM, Built-in Flash, USB or SD
	Number of capturing data 1000 to 10000000 data (*5)
	Sampling up to 1 MS/s (interval 1 us) in built-in RAM, up to 1 kS/s (interval 1 ms) with GBD format in other device, up to 100 S/s (interval 10 ms) with CSV format in other device
Relay	Save data to multiple files with specified capturing time or file size (up to 4 GB) until recording data is stopped
	Destination Built-in Flash, USB or SD
	Sampling up to 1 kS/s (interval 1 ms) with GBD format, up to 100 S/s (interval 10 ms) with CSV format
Data backup	Interval Off, 1, 2, 6, 12, 24 hrs., specific time, or any time with key operation
	Sampling up to 1 kS/s (interval 1 ms) with GBD format, up to 100 S/s (interval 10 ms) with CSV format
	File destination Built-in Flash, USB or SD
Hot-swapping external memory	Hot-swapping USB or SD Flash memory with key operation during data backup
	Search function
	Function Search for specific point in captured data
Search function	Search Analog Signal levels in each channel
	factor Logic 4-channel signal pattern
	Pulse Rising, Falling, Window-in, Window-out in each channel
Search function	Alarm Alarm occurring point
	Calculation function
	Statistical Real-time : Display digital and statistical values at the same time
Scaling (Engineering unit) function	Function : Maximum, Minimum, Peak-to-peak (P-P), Average
	Replay : Statistical values between cursors in replay captured data
	Function : Maximum, Minimum, Peak-to-peak (P-P), Average, RMS
Scaling (Engineering unit) function	Between channels Addition, subtraction, multiplication and division for two analog inputs (only in GBD format)
	Analog voltage Converts using four reference points (gain, offset)
	Temperature Converts using two reference points (offset)
Annotation function	Pulse count Converts using two reference points (gain)
	Comment can be set in each channel, up to 31 alphanumeric characters and symbols (Display first 8 characters on screen)
	Operating environment 0 to 40 °C when driven by AC adapter or battery, 5 to 85 % RH (non condensed)
Power source	AC adapter 100 to 240 V AC, 50/60 Hz
	DC power 8.5 to 24 V DC (required cable option B-514)
	Battery pack Two battery packs (option B-569) required
Power consumption	AC adapter (in 240 V AC) Approx. 39 VA (59 VA while charging battery) with disabling screen saver
	Approx. 34 VA (55 VA while charging battery) with enabling screen saver
	DC drive (24 V) Approx. 0.5 A (0.81 A while charging battery) with disable screen saver
Power consumption	Approx. 0.43 A (0.76 A while charging battery) with enabling screen saver
	DC drive (12 V) Approx. 1 A (Cannot charge battery) with disable screen saver
	Approx. 0.85 A (Cannot charge battery) with enabling screen saver
Power consumption	DC drive (8.5 V) Approx. 1.46 A (Cannot charge battery) with disable screen saver
	Approx. 1.22 A (Cannot charge battery) with enabling screen saver
	External dimensions [WxHxD] Approx. 260 x 161 x 83 mm (with the cover)
Weight	Approx. 1.7 kg (the cover is attached, AC adapter and battery are not included)
	Vibration resistance Compatible with JIS Vibration test method for automobile Type 1 Class A (Vibration durability test: 5 m/s <sup>2</sup> )

Analog input specifications	
Item	Description
Number of input channels	4 channels
Type of input terminal	Isolated BNC connector and Screw terminal (M3.5 screw) (*6)
Input method	All channels isolated unbalanced input, Simultaneous sampling
Sampling speed (interval)	1 M Samples/s to 1 Sample/min (1 µs to 1 min) and External (*7)
Sampling interval	1, 2, 5, 10, 20, 50, 100, 200, 500 µs, 1, 2, 5, 10, 20, 50, 100, 200, 500 ms, 1, 2, 5, 10, 20, 30 sec, 1 min * When using built-in RAM: 1 µs to 1 min, using other storage: 1 ms to 1 min
Frequency response	DC to 200 kHz (within +1/-4 dB)
Measurement range	Voltage (DC) 20, 50, 100, 200, 500 mV, 1, 2, 5, 10, 20, 50, 100, 200, 500, 1000 V, and 1-5V F.S. * Max. rated safety voltage: ± 600 V DC
	DC-RMS (DC coupling and rms value meas.) 10, 25, 50, 100, 250, 500 mV rms, 1, 2.5, 5, 10, 25, 50, 100, 250, 500, 1000 V rms F.S. * Max. rated safety voltage: 600 V rms • Crest Factor : in 1000 V range, up to 1.4 (peak: max. 850 V), in other range, up to 2 • Frequency response : 20 Hz to 10 kHz • Measures the accumulated value of the DC and AC components in effective value, that is a true-RMS.
	Temperature Thermocouple: K, J, E, T, R, S, B, N, W (WRe5-26)
	Humidity 0 to 100 % RH - using the humidity sensor (option B-530)
	Filter (Low pass) Off, Line (1.5 Hz), 5, 50, 500 Hz, 5, 50 kHz (at -3dB, -6dB/oct)
A/D converter	16-bit (effective resolution: 1/40000 of the measuring full range)
Measurement accuracy (*8)	Voltage (DC) ± 0.25% of Full Scale
	Voltage (RMS) ± 1.5% of Full Scale (Sine wave in 20 Hz - 10 kHz)
Temperature	Measurement range
(Thermocouple) (°9)	R/S 0 ≤ TS ≤ 100 °C ± 7.0 °C 100 < TS ≤ 300 °C ± 5.0 °C R: 300 < TS ≤ 1600 °C ± (0.05 % of reading + 3.0 °C) S: 300 < TS ≤ 1760 °C ± (0.05 % of reading + 3.0 °C)
	B 400 ≤ TS ≤ 600 °C ± 5.5 °C 600 < TS ≤ 1820 °C ± (0.05 % of reading + 3.0 °C)
	K -200 ≤ TS ≤ -100 °C ± (0.05 % of reading + 3.0 °C) -100 < TS ≤ 1370 °C ± (0.05 % of reading + 2.0 °C)
	E -200 ≤ TS ≤ -100 °C ± (0.05 % of reading + 3.0 °C) -100 < TS ≤ 800 °C ± (0.05 % of reading + 2.0 °C)
	T -200 ≤ TS ≤ -100 °C ± (0.1 % of reading + 2.5 °C) -100 < TS ≤ 400 °C ± (0.1 % of reading + 1.5 °C)
	J -200 ≤ TS ≤ -100 °C ± 3.7 °C -100 < TS ≤ 100 °C ± 2.7 °C 100 < TS ≤ 1100 °C ± (0.05 % of reading + 2.0 °C)
	N -200 ≤ TS < 0 °C ± (0.1 % of reading + 3.0 °C) 0 ≤ TS < 1300 °C ± (0.1 % of reading + 2.0 °C)
	W 0 ≤ TS ≤ 2315 °C ± (0.1 % of reading + 2.5 °C)
	Reference Junction Compensation (R.J.C.) accuracy: ± 1.0 °C
R.J. Compensation	
	Internal or External
Burnout	Detecting burnout of Thermocouple with menu operation in free-run mode
Input impedance	1 MΩ ±5%
Signal source impedance	up to 1 kΩ
Maximum	Between(+/-) - (-) terminal 20 mV to 2 V range: 30 V DC/AC, 5 V to 1000 V range: 600 V DC/AC
input voltage	Between channels (-) - (-) terminals 600 V DC/AC (CAT III)
	Between channel - GND 600 V DC/AC (CAT III)
Isolation resistance	Min. 50 MΩ (at 500 V DC) with between input and GND
Common-mode rejection ratio	Min. 90 dB (50/60 Hz, signal source impedance: max. 300 Ω)
Signal-noise ratio (S/N)	20 mV range : - 40 dB (when input terminals + and - are shorted) Other range : - 50 dB (when input terminals + and - are shorted)
External input & output signal specifications	
Item	Description
External input/output	Input (*10, *11) Logic or Pulse (4 channels), Trigger or Sampling (1 channel)
	Output (*10, *12) Alarm (4 channels) or Trigger (1 channel) with Alarm (3 channels)
Input signal specification	Logic and Voltage range 0 to +30 V (common ground)
	Pulse Threshold Approx. +2.5 V
	Hysteresis Approx. 0.5 V (+2.5 to +3 V)
External trigger and sampling	Voltage range 0 to +30 V (common ground)
	Threshold Approx. +1.9 V
	Hysteresis Approx. 0.2 V 0.2 V (+1.9 to +2.1 V)
Logic measurement	Measures the status (H or L) of the signal input to each channel
Pulse measurement	Counts pulse signals input to each channel
Pulse count detection cycle	10 µs to 1 hr. (Set separately from analog signal sampling interval)
Maximum pulse input	Maximum input frequency : 100 kHz, Maximum count number : 15 M count (24 bit counter)
Measurement mode	Rotation: Counts the number of pulses per detection cycle and then converts measured value to rotation in rpm • Span: 0 to 500 M rpm/F.S. Accumulating: Accumulates the number of pulses count per detection cycle from the start of measurement • Span: 0 to 20 M count/F.S. Instant: Counts the number of pulses per detection cycle • Span: 0 to 20 M count/F.S.
External trigger input (*10)	Executes specified trigger action
External sampling input (*10)	Executes sampling of measurement signal with each external sampling signal • Maximum input frequency: 100 kHz (Time error: 1 µs or less)
Output signal	Alarm output Open collector (pull-up to 5 V with 10 kΩ resistor) • Maximum load is the 24 V and 100 mA
	Trigger output When a trigger is detected, output terminal releases approximately 500 µs width pulse (Low active)



Software specifications		
Item	Description	
Model name	GL980_2000-APS	
Supported OS (*13)	Windows10, 8.1, 8, 7 (SP1 or later)	
Functions	Control GL980 and GL2000, Real-time data capture, Replay data, and Data format conversion	
Supported device	1 unit of GL980 or GL2000	
Settings control	Input condition, Capturing condition, Trigger/Alarm condition, other	
Transfer of captured data with GL2000	In memory capturing Transfer the captured data to a PC sequentially while data is saved in built-in RAM on GL2000 • Sampling interval: 1 $\mu$ s to 1 min	In real time capturing Transfer the captured data to a PC while data is saved in built-in flash memory, SD or USB on GL2000 • Sampling interval: 1 ms to 1 min saved in GBD and CSV format
Displayed information	Analog waveform, Logic waveform, Pulse count waveform, Digital value	
Display mode	Waveform in Y-T with digital values, Enlarged waveforms, Statistical calculation result values and history, XY graph	
File operation	Converting data format to CSV from GBD binary with data between cursors or all data	
Past data screen function	Displays the current data or past part of data by switching. Available at sampling speed 1 kS/s to 1 S/m (1 ms to 1 min sampling interval)	
Statistical calculation	Maximum, Minimum, Average and Peak-to-peak (p-p) value during data capturing	

#### Battery pack B-569 (option) Specifications

Item	Description
Capacity	7.2 V, 2900 mAh
Battery operating time	Approx. 3 hrs. in displayed signal (LCD: max. brightness) Approx. 5 hrs. in screen saver mode (no display) * When two battery packs are installed in GL2000. Condition: 1 sample per second (1 s), saving captured data to built-in Flash, use two fully charged battery packs, temperature is 25 °C
Method of charging	Charging on GL2000
Charging time	Approx 10 hrs. (charging two batteries)
Other functions	• If an AC power failure occurs, it will automatically switch from the AC adapter to the battery pack. (AC adapter priority use) • When the voltage of the battery pack reaches low, the measurement is automatically stopped after saving data file preserving the accumulated data.

(\*1) It can set for each channel.

(\*2) File size of captured data is up to 4GB in each file.

(\*3) Standard USB memory devices are required.

(\*4) Required minimum capturing time is 15 seconds in GDB format, 30 seconds with CSV format.

(\*5) When using built-in RAM, 10 to 4000000 data

(\*6) Connections can be made individually to BNC terminal or M.35 screw terminal.

(\*7) Required Input/Output cable for GL series (B-513) option for connecting signal.

(\*8) Subject to the following conditions:

- Room temperature is 23 °C ± 5 °C.

- When 30 minutes or more have elapsed after power has turned on.

- Filter is set to Line (1.5 Hz) in DC measurement and temperature.

- GND terminal is connected to ground.

- It is placed vertically.

- Average of the measured values is used.

(\*9) Wire size of Thermocouple used is 0.32mm diameter in the T and K type, and 0.65mm diameter in other types.

(\*10) Required Input/Output cable for GL series (B-513) option for connecting signal.

(\*11) Select either Logic input (4 channels) or Pulse input (4 channels), select either external Trigger input or Sampling input.

(\*12) Select either Trigger output (1 channel) or Alarm output (1 channel).

Available 3 channels Alarm output always.

(\*13) Graphtec does not support software/drive used with operating systems that have become obsolete and are no longer supported by the OS developer.

In the Windows 7, edition of Ultimate, Enterprise, Professional and Home Premium are supported.

#### Standard accessories

- AC adapter with power cable
- CD-ROM (PC application software, User manual)
- Tilt stand set (including mounting screws M4)
- Ferrite core (attach to cable for radiation reduction)
- Quick start guide and Safety guide
- Cover (attached to the main body)
- Screws (M3.5) for input terminal

#### Options and Accessories

Item	Model No.	Description
Input/Output cable for GL	B-513	2 m long (no clip on end of cable)
DC drive cable	B-514	2 m long (no clip on end of cable)
Humidity sensor	B-530	With 3 m long signal cable (with power plug)
Shunt resistor	B-551	250 ohms (Converts signal from "4-20mA" to "1-5V" .)
Battery pack	B-569	Rechargeable Lithium-ion battery (7.2 V, 2900mAh)
Bracket for DIN rail	B-570	Bracket for DIN rail (GL2000 main body), Build-to-order
Cover	B-579	Rubber protector (for replacement)
Carrying case	B-581	Coming soon
Input cable, Safe probe - BNC	RIC-141A	Insulated, 1:1 (42pf), 1.2 m long, 300 V DC, CAT II
Input cable, BNC - BNC	RIC-142	Insulated, 1.5 m long, 1000 V DC, CAT II
Input cable, Banana - BNC	RIC-143	Insulated, 1.6 m long, 600 V DC, CAT II
Clip, Alligator (small size)	RIC-144A	For RIC-143, Aperture 11 mm, 300 V DC, CAT II, Max. 15 A
Clip, Alligator (middle size)	RIC-145	For RIC-143/147, Aperture 20 mm, 1000 V DC, CAT II, Max. 32 A
Clip, Grabber	RIC-146	For RIC-143/147, Aperture 5 mm, 1000 V DC, CAT III, Max. 1 A
Input cable, Banana - BNC (Hi-voltage)	RIC-147	Insulated, 1.6 m long, 1000 V DC, CAT II
Input terminal adapter	SMA-102	Banana (receptacle) to BNC (plug), Insulated
AC Adapter	ACADP-20	Input: 100 - 240 V AC, Output: 24 V DC

Input/Output cable for GL  
B-513      Input cable, Safe probe - BNC  
RIC-141A      Input cable, BNC - BNC  
RIC-142



Clip, Alligator (small size)  
RIC-144A



Clip, Alligator (middle size)  
RIC-145



Clip, Grabber  
RIC-146



Input cable, Banana - BNC  
RIC-143

Humidity sensor  
B-530



Input cable, Banana - BNC (Hi-voltage)  
RIC-147

Shunt resistor  
B-551



- Due to the possibility of equipment or PC failure, the data files on the instrument are not guaranteed to hold memory. Please make a backup of data whenever possible to avoid data loss.

• Brand names and product names listed in this brochure are the trademarks or registered trademarks of their respective owners.

• Specifications and details are subject to change without notice. For additional information, please check our web site or contact your local representative.



Use equipment correctly and safely!

• Use only in accordance with product's user manual.

• To avoid malfunction or an electric shock by current leakage or voltage, please ensure ground connection and use according to the specifications.

**GRAPHTEC**  
Graphtec Corporation

503-10 Shinano-cho, Totsuka-ku, Yokohama 244-8503, Japan  
Tel : +81-45-825-6250 Fax : +81-45-825-6396  
Email : webinfo@graphtec.co.jp

Website <http://www.graphteccorp.com>



[www.calcert.com](http://www.calcert.com)

**CE**

CEI2000 KF10342 1D

[sales@calcert.com](mailto:sales@calcert.com)

1.888.610.7664