

AVO410

Digital Multimeter



- **6000 count backlit digital display**
- **True RMS reading on AC mode**
- **1000 V DC / 750 V AC ranges**
- **10 A AC / DC ranges**
- **Resistance, frequency and capacitance ranges**
- **CAT IV 600 V**

DESCRIPTION

The Megger AVO410 digital multimeter has been designed for the contracting electrician and has the additional features that also make the instrument suitable for wide range of applications and users.

The instrument offers AC and DC voltage and current measurements as well as resistance, frequency and capacitance ranges. True RMS readings on the AC functions are standard on the AVO410 and the instrument features a CATIV 600 V safety rating meaning the instrument is suitable for industrial applications.

The slim, compact case has a tough rubberised holster that provides that extra degree of protection from the extreme conditions found in industrial environments. The style of the case and positioning of the function switch and buttons means the unit sits comfortably in the palm for single handed use.

Continuous references to the user guide have been avoided by the AVO410 utilising simplified functions.

The display features a back light that allows measurements to be made in poorly lit areas.

The AVO410 test leads are supplied with silicon cable and have GS38 compliant shrouded tips on the prods.

Auto-ranging

When first selected, all functions are auto-ranging. A range button on the AVO410 allows multiple manual range selection on each function; a feature that is generally welcomed by many users.

Minimum / Maximum measurements

The instrument has a MIN MAX function that allows the user to switch between minimum and maximum measurements. The

display does not have to be continually monitored to capture a momentary increase or fall in readings.

Data hold

This function allows a displayed result to be frozen on the display which avoids having to remember a measurement value. The hold function can be nested within the MIN MAX feature which stops the AVO410 continuously updating the minimum and maximum measurement values.

Voltage measurements

Both AC and DC voltage measurements up to 750 V and 1000 V respectively are possible with the AVO410, the AC reading being a true RMS value.

Current measurements

For current measurements up to 10 A, a separate fused terminal is provided to protect both user and instrument from excess current.

RS232

The AVO410 has optically isolated RS232 interface that allows the user to connect to a PC via a USB port for data acquisition and analysis. (Optional software is required for this function).

Continuity / diode testing

The continuity function features a buzzer and provides the user both optical and audio indication of identifying and confirming continuity between two points. This function also allows forward and reverse bias testing of diode and semiconductor junctions.

Resistance, capacitance and frequency

Resistance can be measured directly on the ohms range from 0 to 60 MΩ with capacitance measurements from 0 to 6.000 mF. In addition, frequency measurements from 0 to 60 MHz are possible.

SPECIFICATIONS

Display	6000 counts updates 1.5/sec.
Polarity indication	Automatic, positive implied, negative indicated
Over-range indication	“OL” or “-OL”
Low battery indication	Displayed when the battery voltage drops below operating voltage
Auto power off	Approx 10 minutes
Operating ambient	Non-condensing ≤10 °C, 11 °C ~ 30 °C (≤80% R.H) 31 °C ~ 40 °C (≤75% R.H), 41 °C ~ 50 °C (≤45% R.H)
Storage temperature	-20 °C to 60 °C, 0 to 80% R.H. when battery removed from meter
Temperature coefficient	0.15 x (Spec.Acc'y) / °C, <18 °C or >28 °C

Safety

The instrument complies with IEC61010 CATIV 600 V

Power requirements

Standard 9 V battery PP3, NEDA 1604, IEC6F22, JIS006P

Battery life	Alkaline 300 hours
---------------------	--------------------

Dimensions (W x H x D)

76 mm x 158 mm x 38 mm without holster
 82 mm x 164 mm x 44 mm with holster

Weight

522 g

ELECTRICAL SPECIFICATIONS

Accuracy is ± (% reading + number of digits) at 23 °C ±5 °C, less than 80% R.H.

DC / AC Volts

Range	DC accuracy	AC accuracy
600.0 mV	± (0.5% + 2 digits)	50 Hz/60 Hz sine wave only for 600.0 mV range, ± (0.9% +5 digits) 50 Hz ~ 500 Hz *1
6.000		
60.00 V		
600 V		
DC 1000 V/AC 750 V		

Over voltage protection	DC 1000 V or AC
--------------------------------	-----------------

Input impedance	10 MΩ // less than 100 pF
------------------------	---------------------------

CMRR/NMRR

(Common mode rejection ratio/normal mode rejection ratio)

VAC: CMRR >60 dB at DC, 50 Hz/60 Hz

VDC: CMRR >100 dB at DC, 50 Hz/60 Hz

NMRR: >50 dB at DC, 50 Hz/60 Hz

AC conversion type

AC conversions are AC coupled True RMS responding, calibrated to the sine wave input.

*1) The basic accuracy is specified for a sine wave below 4000 counts. Over 4000 counts, add 0.6% to the accuracy. For non-sine waves below 2000 counts, refer to the following for accuracy:

±1.5% addition error for C.F from 1.4 to 3

Crest factor

C.F. = Peak/rms

DC/AC current

Range	DC accuracy	AC accuracy	Voltage burden
600.0 μA	± (1.0% + 2 digits)	N/A	<4 mV/μA
6000 μA			
6.000 A		±(1.5% +6 dgt)	2 V max
10.00 A		50 Hz ~ 500 Hz *1	

Overload protection

A input 10 A (500 V) fast blow fuse

μA input 600 V rms

*1) AC conversion type

Conversion type and additional specification are the same as DC/AC voltage.

Resistance Range	Accuracy	Overload protection
600.0 Ω *2	$\pm (0.7\% + 2 \text{ digits})$	600 V rms
6.000 K Ω		
60.00 K Ω		
600.0 K Ω		
6.000 M Ω $\pm(1.0\% + 2 \text{ digits})$	$\pm (1.0\% + 2 \text{ digits})$	
60.00 M Ω *1	$\pm (1.5\% + 2 \text{ digits})$	

Open circuit voltage -1.3 V approx.

*1 <100 digit rolling

*2 <10 digit rolling

Diode check and continuity

Range	Resolution	Accuracy
Diode	10 mV	$\pm (1.5\% + \text{digits}^*)$

* For 0.4 V ~ 0.8 V

Max. test current 1.5 mA

Max. open circuit voltage 3 V

Overload protection 600 V rms

Continuity

Built-in buzzer will sound when the resistance is less than 500 Ω approx. Response time is 100 ms approx.

Frequency Range	**Sensitivity	Overload protection
6000 Hz	100 mV rms *	Frequency: 0.1% ± 1 digit
60.00 KHz		
600.0 KHz		
6.000 MHz	250 mV rms	
60.0 MHz	1 V rms	

Overload protection 600 V rms

* Less than 20 Hz, the sensitivity is 1.5 V rms

** Max. sensitivity <5 V ac rms

Capacitance

Range	Accuracy
6.000 nF	$\pm (1.9\%) + 8 \text{ digits}$
60.00 nF	
600.0 nF	
6.000 μ F	
60.00 μ F	
600.0 μ F	
6.00 mF*	

Overload protection 600 V rms

* <100 digit of reading rolling

Auto power OFF (APO)

If idle for more than 10 minutes

ORDERING INFORMATION

Item (Qty)	Cat. No.
AVO410 digital multimeter CAT IV 600 V	1001-613
Included accessories	
Test leads and probes	