



Directions:

Spray 4-6 inches from surface to clean. Spray parts while allowing the liquid to flush away flux and flux residue. Use extension brush to remove encrusted residues.

For industrial use only. Read SDS carefully prior to use.

Material Compatibility:

ABS	Poor
Buna-N	Good
EPDM	Poor
Graphite	Good
HDPE	Good
Kynar™	Poor
LDPE	Good
Lexan™	Poor
Neoprene	Fair
Noryl	Good
Nylon™ 66	Good
Cross-linked PE	Good
Polypropylene	Good
Polystyrene	Poor
PVC	Good
Silicone Rubber	Good
Teflon™	Good
Viton™	Good



Product# 8624

12 oz (340g) aerosol / 12 per case



8624 Staticide® A4 All Purpose Flux Remover and Cleaner

Industrial Benchtop Essential

A4 All Purpose Flux Remover and Cleaner is an extra strength solvent that removes most types of fluxes even in areas ordinary brushing cannot reach. Specifically designed to replace chemical formulas using HCFC-141b and AK-225, the A4 formula can remove no-clean and rosin fluxes without using ozone-depleting chemicals and restricted substances.

This essential benchtop flux remover is ideal to use in general industrial settings on motors, generators, metal housings, plugs, sockets, relays, contacts, switches, heat sinks, chip carriers, surface mount devices, and printed circuit boards.

Ideal for the following applications:

- General industrial
- Electronics manufacturing and assembly
- Military defense

FEATURES:

- ✧ Replaces HCFC-141b and AK-225 solvents
- ✧ Removes encrusted, hard, baked-on fluxes and residues
- ✧ Removes oil, grease, ionic, and non-ionic residues
- ✧ Cleans and removes R, RA, RMA, and all synthetic flux residues
- ✧ Non-abrasive, non-flammable, non-corrosive
- ✧ Evaporates quickly; non-residual
- ✧ Ozone safe; contains no CFCs or HCFCs



ACL Inc. registered to
ISO-9001 : 2015
Certificate NO. 10002746

