

30:1 ratio IR thermometer



Functions

- Temp range -76° to 1400°F (-60° to 760°C)
- 30:1 Distance to spot ratio
- Thermocouple input

Features

- Dual laser targeting
- Max/Min/Avg/Diff
- Backlit display
- Auto power off
- Hi/Lo alarm
- Auto-scan
- Thermocouple input
- 3-Year limited warranty

Includes

- Protective boot
- Thermocouple
- Case
- Batteries 2 (AAA)
- Manual

Applications

Check register temperatures
Hard to reach registers and appliances
Faulty breakers and electrical panels
Motors, fans and other moving parts
Boilers, hanging heaters and radiators
Troubleshoot hydronic systems

Q51-673

