

TECHNICAL DATA



Features

- Tests phase orientation of 3-phase power sources
- Indicates phase orientation (clockwise or counter-clockwise) and whether each of the three phases is live
- LEDs display motor rotation and phase status
- Easy to open alligator clips with wide jaws
- Durable double molded plastic housing
- Cat. III 600V safety rating
- Includes three color coded cables, three alligator clips, battery and soft carrying case

R5004-KIT

Phase Rotation/Clamp Meter Kit

Includes:

R5004 Motor Rotation and 3-Phase Tester,
R5040 AC/DC Clamp Meter,
R2990 Thermocouple Adapter,
R5110 Non-Contact Voltage Detector,
TP-01 Beaded Thermocouple Wire Probe,
R1000 Safety Test Lead Set, Double Insulated
and R9950 Carrying Case



Specifications

Nominal Voltage	1 to 400V AC
Rotary Direction:	
Nominal Voltage Phase Indirection:	120 to 400V AC
Frequency:	2 to 400Hz

General Specifications

Power Supply:	9V Battery
Battery Life: Overvoltage	Approx. 1 year (regular usage)
Category: Product	CAT. III 600V, CAT. IV 300V CE
Certifications:	0 to 122°F (0 to 50°C)
Operating Temperature:	-4 to 140°F (-20 to 60°C)
Storage Temperature:	
Operating Humidity Range:	10 to 80%
Dimensions:	5.1 x 2.7 x 1.3" (130 x 68 x 32 mm)
Weight:	4.5oz (130g)

Model	Description
R5004	Motor Rotation and 3-Phase Tester
CA-05A	Soft Carrying Case
R1210	Alligator Clip Set, Large
R5004-KIT	Phase Rotation/Clamp Meter Kit
R5004-NIST	Motor Rotation and 3-Phase Tester & NIST