## Accessories

### Decade Boxes

#### Use Model RDB-10 to:

- Select resistance in series or in parallel combinations
- Substitute resistance in servicing applications
- Vary resistance levels in circuitry design
- Determine impedance, reactance and frequency characteristics
- Ideal for classroom education
- Demonstrate Ohm's Law and other effects by varying resistance

# Model RDB-10 Resistance Decade Box



#### Features:

- Calibrate test equipment with its high accuracy of 1%
- 28 switches organized in a clean 4 x 7 grid for easy use
- All switches clearly display a visible white dot when in the ON position
- Includes a protective rubber holster with tilt-stand for ease of use and viewing
- Ideal for service, prototype and experimental and educational use
- Set at any resistance value from 1 ohm to 11 Megohms in one ohm increments
- Input terminals accept standard banana plugs, bare wires, spade lugs or alligator clips
- One Year Warranty



**Innovative Training Solutions** 

Model RDB-10 is a hand held box Resistance decade that creates a specific resistance value using a combination of switches. Designed with accuracy to meet industry needs the of and education alike.

The RDB-10 is compact, а convenient tool for aiding in engineering design and testing as calibration well as of test equipment.

It offers 7 decades of resistance ranges, from 1  $\Omega$  to over 11  $M\Omega$ in 1  $\Omega$  steps. Easy-to-use slide switches allow for straightforward addition and subtraction resistance values. RDB-10 is a passive device that requires no power source.

### **Specifications**

Resistance ranges: 1  $\Omega$  to 11,111,110  $\Omega$ 

in 1 Ω steps

Internal Resistance:  $0.3 \Omega$ 

Power: 1 Watt Resistors Connection: 2 binding posts

Accuracy:

Operating conditions

Temperature: 32 to 122 °F (0 to 50 °C)

Humidity: < 80%RH

6" x 3.7" x 1.9" Dimensions: Weight Approx.: 0.95 lbs.



1.888.610.7664